Aircaster Guest Panel

Remote cough and talkback panel for guest positions



Aircaster Guest Panel dimensions

Overview

Every mic module in the Aircaster M12 mixer has a REMOTE TRS jack for connection to a remote Guest Panel. The panel contains a single illuminating momentary-action pushbutton, mounted on a perspex panel designed for insertion into a standard 60 mm desktop cable tidy.

The switch is pre-wired to a TRS socket, allowing direct connection to any mic module\u2019s REMOTE socket via a standard TRS jack-to-jack cable.

How It Works

Fader DOWN \u2014 Talkback mode

When the corresponding channel fader is down, pressing the Guest Panel button activates the PF (pre-fade) function on the mic module, allowing talkback from the guest position to the mixer operator. The module\u2019s blue PF LED flashes to alert the operator.

Fader UP \u2014 Cough mode

When the corresponding channel fader is up, the Guest Panel button illuminates, alerting the guest that their microphone is live. Pressing the button temporarily mutes audio in the mic module and flashes the green MIC ON LED in the channel strip, alerting the mixer operator that a cough action is taking place.

Connection

The TRS jack carries both switch and LED connections on a single cable, keeping installation simple.

Specifications

Panel diameter	60 mm (fits standard cable tidy)
Depth below desk	30 mm
Button type	Illuminating momentary action
Connection	Pre-wired TRS socket
Cable required	TRS jack to jack (not supplied)
Compatible with	All Aircaster M12 mic module REMOTE outputs

The Aircaster Guest Panel is designed for use with the Aircaster M12 broadcast mixer.

For further information: **sales@klotzmediasolutions.com**