MIC-ON Wall Mount Indicator

Highly visible mic-live indicator for broadcast studios



Overview

The MIC-ON wall mount indicator is a highly visible wall-mounting mic live indicator, with a choice of display modes — solid ON, fast flash or slow flash.

Control

Can be driven directly from the Klotz Media Solutions Aircaster M12 broadcast mixer, without the need for an external power supply, or from other makes of mixer which present a make pair of contacts, in which case an external supply is required.

Alternatively, if the mixer provides a power output, this can control the indicator directly.

Power Requirements

9–18V DC, approx. 50mA from 12V.

Connections

There are three screw terminal blocks located at the top of the unit (can be at the bottom by simply rotating the cover):

- **4-way** — for connection from an Aircaster or mixer providing ‘make’ contacts
- **3-way** — for connection from an external power supply (if required)
- **2-way** — a ‘link’ output to power a second indicator e.g. for inside and outside of a studio door, controlled from the same feed

Set-up

A bank of 5 piano-key switches, located next to the connectors, allows selection of display mode, control and power options.

Dimensions

155 × 220 × 60 mm

These products are designed and assembled in the UK by Synergy Digital Ltd, marketed under the Klotz Media Solutions brand.

For further information: **sales@klotzmediasolutions.com**

© Klotz Media Solutions Ltd • klotzmediasolutions.com